## 1000AC Digital Clamp Meter | 205A

205A is a professional digital clamp meter with 40mm jaw. It is ergonomically designed, allowing better handling for users wearing electrical gloves. 205A is a great choice for electrical professionals in need of measuring up to 1000A AC current. The meter is an ideal tool for maintenance in smelting, manufacturing, petroleum, electric power, chemical and other industries.

## Features :

Economy

- 1000A AC current, 3/s sampling rate
- 4000 Display count, Auto polarity indication
- LCD Backlight, Duty cycle
- Low battery indication
- Data hold, Auto power off



## Ily a c g,

Complies to: IEC61010

Specifications :

Auto Range	$\checkmark$	
True RMS	_	
Display Count	4000	
Jaw Size	40mm	
Measurements		Accuracy
AC Current (A)	1000A	± (1.5%+5)
AC Voltage (V)	600V	± (1.2%+5)
DC Voltage (V)	600V	± (0.8%+1)
Resistance (Ω)	40ΜΩ	± (1%+2)
Frequency (Hz)	10Hz~10MHz	± (0.1%+3)
Other Features		
Duty Cycle	$\checkmark$	
Diode Test	$\checkmark$	
Auto Power Off	$\checkmark$	
Continuity Buzzer	$\checkmark$	
Low Battery Indication	$\checkmark$	
Data Hold	$\checkmark$	
LCD Backlight	$\checkmark$	
Full Icon Display	$\checkmark$	
Input Impedance For DCV (Around 10mΩ)	$\checkmark$	
Category Safety Ratings	CAT III 300V, CAT II 600V	
General Characteristics		
Power	9V Battery (6F22)	
Display	37mm x 18mm	
Product Net Weight	350g	
Product Size	236mm x 97mm x 40mm	
Standard Accessories	Battery, Test Leads, Carrying Bag	

## STANLAY

Asian Contec Ltd. Asian Center, B-28, Okhla Industrial Area, Phase-1, New Delhi -110020, India. Contact Nos. : Tel : +91-11-41860000 (100 Lines), Direct Sales Helpline : +91-11-41406926 Web : www.stanlay.in www.stanlay.com email: sales@stanlay.com Regional Offices : • Faridabad • Mumbai • Bengaluru • Hyderabad • Bhubaneshwar • Guwahati

