2000A AC/DC Clamp Meter | 221

221 is an AC/DC digital clamp meter which ensures stable performance, safety, and reliability for measuring up to 2000A AC and DC current. It is designed with over-load protection for all ranges, perfect for professionals measuring high currents. It sports a large jaw of 63mm to allow use on thicker wires.

Features:

- AC/DC current measurement, Data hold, LCD backlight
- True RMS, Auto range
- MAX/MIN/REL modes, Zero mode
- Inrush current Low pass filtering, Analog bar graph
- The current signal can be converted to a voltage signal output signal















Complies to: Gb4793 IEC/EN61010-1 IEC/EN61010-2-032 IEC/EN61010-2-033









Specifications:

Auto Range	$\sqrt{}$	
True RMS (AC Voltage/AC Current)	$\sqrt{}$	
Display Count	6000	
Jaw Size	63mm	
Measurements	Range	Accuracy
AC Current (A)	2000A	± (2.5%+5)
DC Current (A)	2000A	± (2.5%+5)
AC Voltage (V)	750V	± (1.2%+5)
DC Voltage (V)	1000V	± (0.8%+1)
Resistance (Ω)	66ΜΩ	± (1%+2)
Frequency (Hz)	20MHz	± (0.1%+3)
Other Features		
Duty Cycle	$\sqrt{}$	
Diode Test	J	
Continuity Buzzer	J	
Low Pass Filter	J	
Inrush Current	J	
Relative Mode	$\sqrt{}$	
Data Hold/Max	$\sqrt{}$	
MIN/I-OUT Function	$\sqrt{}$	
Analog Bar Graph	66 Data Sets	
Full Icon Display	$\sqrt{}$	
Low Battery Indication	J	
Input Impedance ≥10mΩ	$\sqrt{}$	
Category Safety Ratings	CAT III 1000V, CAT IV 600V	
General Characteristics		
Power	9V Battery (6F22)	
Display	43mm x 30mm	
Product Net Weight	726g	
Product Size	298mm x 107mm x 47mm	
Standard Accessories	Test Leads, Output Cable	



Asian Contec Ltd.

Asian Center, B-28, Okhla Industrial Area, Phase-1, New Delhi -110020, India.

Contact Nos.: Tel: +91-11-41860000 (100 Lines), Direct Sales Helpline: +91-11-41406926

Web: www.stanlay.in www.stanlay.com email: sales@stanlay.com

Regional Offices: • Faridabad • Mumbai • Bengaluru • Hyderabad • Bhubaneshwar • Guwahati



