Non-Contact AC Voltage Detector | 12A



12A is a non-contact AC voltage detector. It is lightweight and convenient to carry due to its pocket size. The device can detect electricity when it is close in range of live adapters, connection terminals, or wires. The voltage detector can be used in residential, commercial, and industrial settings.



Complies To: EN61010-1 UL61010-1 CASC 22.1 No. 61010-1





Specifications:

AC Voltage	90V~1000V
Frequency	50Hz/60Hz
Buzzer	J
Low Battery Indication ≤2V	$\sqrt{}$
LED Flashlight	\downarrow
Auto Power Off	$\sqrt{}$
Operation	Manual
Category Safety Ratings	CAT IV 1000V
General Characteristics	
Power	1.5V Battery (R03) x 2
Product Net Weight	50g
Product size	150mm x 20mm
Standard Accessories	Batteries





Asian Contec Ltd

Asian Center, B-28, Okhla Industrial Area, Phase-1, New Delhi -110020, India. Contact Nos.: Tel: +91-11-41860000 (100 Lines), Direct Sales Helpline: +91-11-41406926

Web: www.stanlay.in www.stanlay.com email: sales@stanlay.com

Regional Offices: • Faridabad • Mumbai • Bengaluru • Hyderabad • Bhubaneshwar • Guwahati

