

EARTH GROUND TESTER | SET500

Earth Ground Tester measures earth resistance in 3 ranges SET500 Earth tester can (20Ω , 200Ω , 2000Ω) with data logging facility.

Features:

- Precise 3 wire earth resistance measurement
- Simple 2 wire earth resistance measurement
- Hold save function
- Data logging

Specifications:



Measurement	Range	Accuracy
Display count	200	
Earth Resistance Testing (Ω)	0~20Ω	±2% ±10Ω
	0~200Ω	±2% ±3
	0~2000Ω	±2% ±3
AC Earth Voltage (V)	0~200	±(1%+4)
Manual Ranging	√	√
LCD Backlight Display	√	√
Battery Check & Auto Power Off	√	√
Overload Protection	√	
Data Logging	20	√
Over-Range Display	Display “OL”	√
Poor Contact Display		√
Simple 2-Wires Testing		√
Precision 3-Wires Testing		
Double Insulation Protection		
Category Safety Rating	CAT III 600V (IEC 61010-1),IEC 61557-1.5, IEC 61010-2-31	
General Characteristics		
Power	1.5V Alkaline Battery (AA) x 6	
Display	70.6 x 34 mm	
Product Net Weight (g)	560 g	
Product Size	160mm x 100mm x 70.5 mm	
Product Supply	Earth Ground Tester Unit, 1.5V Alkaline Battery, Test Lead (Green + Yellow + Red), Simple Test Lead, Test Probe 2 pcs, User Manual & Carry Bag	



Economy

