

i520 MULTI SCANNER

Locate PVC & Metal Conduits, Hot Electric Wiring, Electric Boxes In Wall, Tile & Concrete

Description :

MultiScanner i520 OneStep quickly and easily locates conduits behind walls, floors, and ceilings. It also locates metal as well as live AC electrical wiring.

Features :

- A 4-mode switch makes it easy to change functions, while the ultra-bright display screen, SpotLite® Pointing System, and audio tone all indicate the location of the target
- The signal strength indicator helps to distinguish between shallow and deep targets
- Stud Scan mode locates the edges and center of PVC conduits, wood or metal conduits studs up to ¾ inch (19 mm) deep
- DeepScan® mode doubles the scanning depth to 1½ inches (38 mm)
- AC Scan finds and traces live, unshielded electrical wire up to 2 inches (51 mm) deep
- Metal Scan mode locates nonferrous metal such as copper pipe up to 1½ inches (38 mm) deep, and ferrous metal & ferrous pipes such as rebar up to 3 inches (76 mm) deep
- WireWarning® detection indicates the presence of live, unshielded electrical wire up to 2 inches (51 mm) deep in stud and metal scanning modes
- ACT™ (Auto Correcting Technology) corrects common user errors automatically, such as when scanning begins over a stud



Specifications :

Measurement Depth	Up to 38 mm(1.5 inch) for PVC conduits in stud scan mode
	Up to 38 mm (1.5inch) for copper in metal scan mode
	Up to 76 mm (3inch) for rebar pipes in metal scan mode
	Up to 51 mm for AC wires 95-250V at 50Hz
Power Supply	1 x 9V Battery
Size (in mm)	184 x 81 x 36
Weight (in g)	226
Environmental	Water & Splash Proof resistant, not water proof

Item Code: ST-i520



Product Supply Includes: i520 Unit, Carry Case & 1 x 9V Battery